

Wire Tracker: NF-268

Item Specifics:

Is_customized : Yes
Brand Name : Noyafa
Model Number : NF-268
Place of Origin : Shenzhen.China
Main Function : Test and Track Cables
Tracking Type : UTP/STP RJ45 (8P4C 8P8C), RJ11, BNC
Other Function : Tone trace breakage points
Power : 9V Alkaline battery
Warranty : 1 Year

Features:

- 1. Quickly tracing & find Lan/telephone/coax cable which is connected with switch or router.
- 2. Check wiremap of Lan cable with receiver directly after it is found.
- 3. Tone tracing breakge points of Lan cables and metal lines
- 4. Noise avoidable, working better against electromagnetic interference even connected to switch or router.
- 5. RJ45/RJ11/BNC and other ports are included and the complex switch is not required.
- 6. Endurable high pressure and self-protection ability.

Technical indexes:

NF-268 Transmitter specifications	
Tone frequency	130kHz
Max. distance of transmission	More than 3 kilometers
Max. working current	Less than 10mA
Tone mode	2 Tones, adjustable
Compatible connectors	RJ11, RJ45,BNC
Max. signal voltage	8Vp-p
Function and faults light display	Light display(Wiremap, tone,tracing)
Voltage protection	AC 60V/DC 42V
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V x 1pcs)
Dimension(LxWxD)	13x4x2cm
NF-268 Receiver specifications	
Frequency	130kHz
The Max. working current	Less than 30mA
Earjack	1
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimension(LxWxD)	10 x 5 x 2.3cm

Attention:

1. Don't connected high voltage lines to avoid burning out the machine.
2. Put into the right place to avoid hurting others, because of the sharp part.
3. Connected the cable to the right port.
4. Read the user manual before use it.

Standard carton:

Carton size: 51x33x51 cm

Quantity : 40pcs/ctn

Weight: 18 KG