

## Wire Tracker: NF-168S

### Item Specifics:

Is\_customized : Yes

Brand Name : Noyafa

Model Number : NF-168S

Place of Origin : Shenzhen.China

Main Function : Test and Track Cables

Tracking Type : UTP/STP RJ45 (8P4C 8P8C), RJ11, BNC

Other Function : Tone trace breakage points

Power : 9V Alkaline battery(not included)

Warranty : 1 Year



### Features:

1. Quickly tracing & find Lan/telephone/coax cable which is connected with switch or router.
2. Two scan modes selectable: AC filter & Non AC filter
3. Check wiremap of Lan cable with receiver directly.
4. Tone tracing breakage points of Lan cables and metal lines.

### Technical indexes:

NF-168S Transmitter specifications	
Tone frequency	455K Hz
Max. distance of transmission	More than 3 kilometers
Max. working current	Less than 80mA
Tone mode	2 Tones, adjustable
Compatible connectors	RJ11, RJ45,BNC
Max. signal voltage	8Vp-p
Function and faults light display	Light display(Wiremap, tone,tracing)
Voltage protection	DC 48V
Dimension(LxWxD)	13x4x2cm
NF-168S Receiver specifications	
Frequency	455 KHz
The Max. working current	Less than 100mA
Earjack	1pcs
Dimension(LxWxD)	10 x 5 x 2.3cm

### Standard carton:

Carton size: 51x33x51 cm

Quantity : 40pcs/ctn

Weight: 18 KG