

**Wire tracker : NF-801R**

**Item Specifics:**

Is\_customized: **Yes**

Brand Name: **Noyafa**

Model Number: **NF-801R**

Place of Origin: **Shenzhen.China**

Port: **RJ11/ RJ45**

Tracing type: **UTP/STP RJ45, RJ11 and metal cable**

Testing Type:**Shield and unshiled RJ45 (8P8C)**

Power: **9V Alkaline battery**

Certificates: **CE/ FCC**

Warranty: **1Year**

**Main functions:**

1. Quickly trace and identify cables among lots of unknown cables.
2. Check continuity of Lan cables.
3. Track the cables or wires, and diagnose the breakage.
4. Endurable and prevent of burnout.
5. Visible indication: pin-to-pin cable map for individual cable (not by pairs).
6. Low Voltage alarm function.
7. Earphone permits use in noisy environments.
8. LED light assists use in dark corners.

**Technical parameters:**

NF-801 Transmitter specifications	
Tone frequency	1000Hz
Max. distance of transmission	2000m
Max. working current	Less than 10mA
Volume Regulate Function	Audio volume level control
Tone mode	2 Tones, adjustable
Compatible connectors	RJ11,RJ45
Max. signal voltage	8Vp-p

LED lights display	Wiremap, tone, tracing
Battery Type	DC9.0V ( NEDA 1604/6F22) x 1pc
Dimensions (LxWxD)	15 x 3.7 x 2cm
NF-801 Receiver specifications	
Frequency	1000Hz
The Max. working current	Less than 30mA
Earphone jack	1
Battery Type	DC9.0V ( NEDA 1604/6F22) x1pc
Dimensions (LxWxD)	12.2 x 4.5 x 2.3cm

**Attention:**

1. Don't connected high voltage lines to avoid burning out the machine.
2. Put into the right place to avoid hurting others, because of the sharp part.
3. Connected the cable to the right port.
4. Read the user manual before use it.

**Standard carton:**

Carton size: 51x33x51cm

Quantity: 40pcs/ctn

Weight: 16.2kg